

FROM DOS.

Type **EDIT** <enter>

In Blue Screen

Type ~CC¬ ¬XA¬JUS¬XZ

Note. The ~CC¬ changes the command character to Logical Not immediately upon receipt so the remaining ZPL commands must be preceded by the newly changed command character. In this case the JUS command is saving the change to the printer memory.

To get the ¬ (Logical not character) to pop up, hold the ALT key and type 170 from the keypad on the right hand side of the keyboard.

Depress <ALT+F> and save files as 1.ZPL

Exit back to DOS

If sending via Serial Port (COM2 in this example):

Type **MODE COM2:96,N,8,1,P** <enter> (make sure these comm parameters match your printer baud, parity, data bits, stop bits)

Type **COPY 1.ZPL COM2** <enter>

or

If sending via Parallel Port:

Type **COPY 1.ZPL LPT1**<enter>

Verify that datalight flashes.

Verify 'format prefix' has to AAH on printer configuration label.