

Table 7 • Print Settings (Continued)

<p>Reprint Mode</p>	<p>When reprint mode is enabled, you can reprint the last label printed by pressing and holding PAUSE + CANCEL on the printer's control panel.</p> <table border="1"> <tr> <td data-bbox="378 331 760 415"><i>Accepted values:</i></td> <td data-bbox="760 331 1429 415"> <ul style="list-style-type: none"> • ON • OFF </td> </tr> <tr> <td data-bbox="378 415 760 464"><i>Related ZPL command(s):</i></td> <td data-bbox="760 415 1429 464">^JZ</td> </tr> <tr> <td data-bbox="378 464 760 512"><i>SGD command used:</i></td> <td data-bbox="760 464 1429 512">ezpl.reprint_mode</td> </tr> <tr> <td data-bbox="378 512 760 560"><i>Control panel menu item:</i></td> <td data-bbox="760 512 1429 560">REPRINT MODE</td> </tr> <tr> <td data-bbox="378 560 760 611"><i>Printer web page:</i></td> <td data-bbox="760 560 1429 611">N/A</td> </tr> </table>	<i>Accepted values:</i>	<ul style="list-style-type: none"> • ON • OFF 	<i>Related ZPL command(s):</i>	^JZ	<i>SGD command used:</i>	ezpl.reprint_mode	<i>Control panel menu item:</i>	REPRINT MODE	<i>Printer web page:</i>	N/A
<i>Accepted values:</i>	<ul style="list-style-type: none"> • ON • OFF 										
<i>Related ZPL command(s):</i>	^JZ										
<i>SGD command used:</i>	ezpl.reprint_mode										
<i>Control panel menu item:</i>	REPRINT MODE										
<i>Printer web page:</i>	N/A										
<p>Maximum Label Length</p>	<p>Set the maximum label length to a value that is at least 1.0 in. (25.4 mm) greater than the actual label length plus the interlabel gap. If you set the value to one that is smaller than the label length, the printer assumes that continuous media is loaded, and the printer cannot calibrate.</p> <p>For example, if the label length is 6.0 inches (152 mm) including the interlabel gap, set the parameter for at least 7.0 inches (178 mm).</p> <div data-bbox="646 863 1166 1419" data-label="Diagram"> </div> <table border="1"> <tr> <td data-bbox="524 1430 618 1472">1</td> <td data-bbox="618 1430 1281 1472">Label length (including interlabel gap)</td> </tr> <tr> <td data-bbox="524 1472 618 1514">2</td> <td data-bbox="618 1472 1281 1514">Interlabel gap</td> </tr> <tr> <td data-bbox="524 1514 618 1577">3</td> <td data-bbox="618 1514 1281 1577">Set the maximum label length to approximately this value</td> </tr> </table>	1	Label length (including interlabel gap)	2	Interlabel gap	3	Set the maximum label length to approximately this value				
1	Label length (including interlabel gap)										
2	Interlabel gap										
3	Set the maximum label length to approximately this value										
	<table border="1"> <tr> <td data-bbox="378 1587 760 1640"><i>Accepted values:</i></td> <td data-bbox="760 1587 1429 1640">0 to the maximum label length supported by the printer</td> </tr> <tr> <td data-bbox="378 1640 760 1692"><i>Related ZPL command(s):</i></td> <td data-bbox="760 1640 1429 1692">^ML (Example for 203dpi) 7" = ^ML1421</td> </tr> <tr> <td data-bbox="378 1692 760 1745"><i>SGD command used:</i></td> <td data-bbox="760 1692 1429 1745">ezpl.label_length_max</td> </tr> <tr> <td data-bbox="378 1745 760 1797"><i>Control panel menu item:</i></td> <td data-bbox="760 1745 1429 1797">LABEL LENGTH MAX (ZT230)</td> </tr> <tr> <td data-bbox="378 1797 760 1864"><i>Printer web page:</i></td> <td data-bbox="760 1797 1429 1864">View and Modify Printer Settings > Media Setup > Maximum Length</td> </tr> </table>	<i>Accepted values:</i>	0 to the maximum label length supported by the printer	<i>Related ZPL command(s):</i>	^ML (Example for 203dpi) 7" = ^ML1421	<i>SGD command used:</i>	ezpl.label_length_max	<i>Control panel menu item:</i>	LABEL LENGTH MAX (ZT230)	<i>Printer web page:</i>	View and Modify Printer Settings > Media Setup > Maximum Length
<i>Accepted values:</i>	0 to the maximum label length supported by the printer										
<i>Related ZPL command(s):</i>	^ML (Example for 203dpi) 7" = ^ML1421										
<i>SGD command used:</i>	ezpl.label_length_max										
<i>Control panel menu item:</i>	LABEL LENGTH MAX (ZT230)										
<i>Printer web page:</i>	View and Modify Printer Settings > Media Setup > Maximum Length										